



# Hearty Homestyle Dog Feast



\*Use the 12 mm extrusion die.

	Ingredient	Group	Ratio%	Volume Equivalent
24 oz.	Beef Top Round or Ground Beef	Protein	18%	3.00 cups
16 oz.	Chicken Breast	Protein	12%	2.00 cups
16 oz.	Pork Shoulder or Butt (boneless)	Protein	12%	2.00 cups
10 oz	Carrots	Vegetable	8%	1.25 cups
10 oz	Celery	Vegetable	8%	1.25 cups
10 oz.	Sweet Potato	Vegetable	8%	1.25 cups
8 oz.	Peas (frozen)	Vegetable	6%	1.00 cup
8 oz.	White Button Mushrooms	Vegetable	6%	1.00 cup
1.5 cups	Barley	Grain	9%	1.50 cups
1.5 cups	Stock or Water	Liquid	9%	1.25 cups
1 tbsp.	Olive Oil	Oil	0%	1 tbsp.
4 oz.	Chia Seeds	Fiber	3%	0.50 cup
<b>Total: 130.5 oz. ( 7 lb. 9 oz.) or 16 1/3 cups</b>			<b>100%</b>	<b>16.31 cups</b>

## Beef Operation

Beef: 45 minutes

- Cut ingredients into 3/4"-1" size pieces.
- Measure ingredients to the amounts listed in the recipe using the measuring cups provided.
- Assemble the unit for use.
- Load the ingredients in the following order: **Liquid, Grains, Proteins, Vegetables, Chia Seeds.**
- Close the Lid.
- Plug unit into a grounded 120v electrical outlet.
- Press the **Power On Button**. 
- Press the **Menu Button**  to select food type. Press to highlight **Beef**. 
- Press the **Start Button**. 
- The unit will begin to heat — once the correct temperature is achieved, the cooking timer will start automatically.
- Once the Cooking cycle completes, the Unit will beep.
- Place a round bowl of 4" height/2-3 quarts under the output.
- Press **Mix/Dispense Button**.  The Unit will mix and then automatically reverse direction and dispense the food.
- Rotate the bowl as food dispenses to prevent overspill.
- When dispensing is complete, open the lid and check for any remaining mixture. Scrape if needed.
- If food remains, Close the lid, press the **Dispense**  button, then press **Start**  to finish.
- Once the unit cools down, disassemble the parts and wash them thoroughly.